


### Features

- STM32F429ZIT6 microcontroller featuring 2 Mbytes of Flash memory, 256 Kbytes of RAM in an LQFP144 package
- On-board ST-LINK/V2 on STM32F429I-DISCO (old order code) or ST-LINK/V2-B on STM32F429I-DISC1 (new order code)
- mbed™-enabled (see <http://mbed.org>) with the new order code only
- USB functions:
  - Debug port
  - Virtual COM port (with new order code only)
  - Mass storage (with new order code only)
- Board power supply: through the USB bus or from an external 3 V or 5 V supply voltage
- 2.4" QVGA TFT LCD
- 64-Mbit SDRAM
- L3GD20, ST-MEMS motion sensor 3-axis digital output gyroscope
- Six LEDs:
  - LD1 (red/green) for USB communication
  - LD2 (red) for 3.3 V power-on
  - Two user LEDs: LD3 (green), LD4 (red)
  - Two USB OTG LEDs: LD5 (green) VBUS and LD6 (red) OC (over-current)
- Two push-buttons (user and reset)
- USB OTG with micro-AB connector
- Extension header for LQFP144 I/Os for a quick connection to the prototyping board and an easy probing
- Comprehensive free software including a variety of examples, part of STM32CubeF4 package or STSW-STM32138, for using legacy standard libraries



1. Picture is not contractual.

### Description

The 32F429IDISCOVERY kit leverages the capabilities of the STM32F429 high-performance microcontrollers, to allow users to easily develop rich applications with advanced Graphic User interfaces.

With the latest board enhancement, the new STM32F429I-DISC1 order code has replaced the old STM32F429I-DISCO order code.



## System requirements

- Windows® OS (XP, 7, 8)
- USB Type-A to Mini-B cable

## Development toolchains

- IAR® EWARM (IAR Embedded Workbench®)
- Keil® MDK-ARM™
- GCC-based IDEs (free AC6: SW4STM32, Atollic® TrueSTUDIO®,...)
- ARM® mbed™ online

## Demonstration software

The demonstration software is preloaded in the MCU Flash memory. It displays on the screen icons to run different applications: clock/calendar, a game, a video player and an image browser, performance monitoring and system information.

The latest versions of the demonstration source code and associated documentation can be downloaded from the [www.st.com/stm32f4-discovery](http://www.st.com/stm32f4-discovery) webpage.

## Product marking

Tools marked as "ES" or "E" are not yet qualified and as such, they may be used only for evaluation purposes. ST shall not be liable for any consequences related with other ways of use of such non-qualified tools, for example, as reference design or for production.

Examples of location of "E" or "ES" marking:

- on target STM32 microcontroller part mounted on the board (for illustration, refer to section "Package information" of a STM32 datasheet at [www.st.com](http://www.st.com))
- next to the evaluation tool ordering part number, as a label stuck or a silk-screen printed on the board

## Ordering information

To order the Discovery kit for the STM32F429 line of microcontrollers, refer to [Table 1](#).

**Table 1. List of the order codes**

Order code	ST-LINK version
STM32F429I-DISCO	ST-LINK/V2
STM32F429I-DISC1	ST-LINK/V2-B

## Revision history

**Table 2. Document revision history**

Date	Revision	Changes
06-Sep-2013	1	Initial version.
29-Sep-2014	2	Updated <a href="#">Section : Features</a> and <a href="#">Section : Description</a> to introduce STM32cubeF4 and STSW-STM32138. Updated ST MEMS feature. Updated <a href="#">Section : System requirements</a> and <a href="#">Section : Development toolchains</a> .
23-Oct-2015	3	Updated <a href="#">Section : Features</a> , <a href="#">Section : Description</a> , <a href="#">Section : Product marking</a> .
28-Oct-2016	4	Updated <a href="#">Section : Features</a> and <a href="#">Section : Description</a> to inform that the new STM32F429I-DISC1 order code has replaced the old STM32F429I-DISCO order code.

**IMPORTANT NOTICE – PLEASE READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2016 STMicroelectronics – All rights reserved