NTMFS4841N

Power MOSFET
30 V, 57 A, Single N−Channel, SO−8FL

Features
- Low $R_{DS(on)}$ to Minimize Conduction Losses
- Low Capacitance to Minimize Driver Losses
- Optimized Gate Charge to Minimize Switching Losses
- These are Pb−Free Devices

Applications
- Refer to Application Note AND8195/D
- CPU Power Delivery
- DC−DC Converters

MAXIMUM RATINGS (T_J = 25°C unless otherwise stated)

Parameter			Symbol	Value	Unit
Drain−to−Source Voltage			V_{DSS}	30	V
Gate−to−Source Voltage			V_{GS}	±20	V
Continuous Drain Current $R_{\theta JA}$ (Note 1) Steady State	Steady State	T_A = 25°C	I_D	13.1	A
		T_A = 85°C		9.5	
Power Dissipation $R_{\theta JA}$ (Note 1)		T_A = 25°C	P_D	2.17	W
		T_A = 85°C		1.13	
Continuous Drain Current $R_{\theta JA}$ − t = 10 sec		T_A = 25°C	I_D	19.9	A
		T_A = 85°C		14.4	
Power Dissipation $R_{\theta JA}$, t ≤ 10 sec		T_A = 25°C	P_D	5	W
		T_A = 85°C		2.6	
Continuous Drain Current $R_{\theta JA}$ (Note 2)		T_A = 25°C	I_D	8.3	A
		T_A = 85°C		6	
Power Dissipation $R_{\theta JA}$ (Note 2)		T_A = 25°C	P_D	0.87	W
		T_A = 85°C		0.45	
Continuous Drain Current $R_{\theta JC}$ (Note 1)		T_C = 25°C	I_D	57	A
		T_C = 85°C		41	
Power Dissipation $R_{\theta JC}$ (Note 1)		T_C = 25°C	P_D	41.7	W
		T_C = 85°C		21.7	
Pulsed Drain Current	t_p=10μs	T_A = 25°C	I_{DM}	171	A
Operating Junction and Storage Temperature			T_J, T_{STG}	−55 to +150	°C
Source Current (Body Diode)			I_S	35	A
Drain to Source dV/dt			dV/dt	6	V/ns
Single Pulse Drain−to−Source Avalanche Energy (V_{DD} = 24 V, V_{GS} = 10 V, I_L = 19 A_{pk}, L = 1.0 mH, R_G = 25 Ω)			EAS	180	mJ
Lead Temperature for Soldering Purposes (1/8" from case for 10 s)			T_L	260	°C

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

ON Semiconductor®

http://onsemi.com

$V_{(BR)DSS}$	$R_{DS(ON)}$ MAX	I_D MAX
30 V	7.0 mΩ @ 10 V	57 A
	11.4 mΩ @ 4.5 V	



N−CHANNEL MOSFET



SO−8 FLAT LEAD CASE 488AA STYLE 1

MARKING DIAGRAM



A = Assembly Location
Y = Year
W = Work Week
ZZ = Lot Traceability

ORDERING INFORMATION

Device	Package	Shipping†
NTMFS4841NT1G	SO−8FL (Pb−Free)	1500 / Tape & Reel
NTMFS4841NT3G	SO−8FL (Pb−Free)	5000 / Tape & Reel

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

THERMAL RESISTANCE MAXIMUM RATINGS

Parameter	Symbol	Value	Unit
Junction−to−Case (Drain)	$R_{\theta JC}$	3	°C/W
Junction−to−Ambient − Steady State (Note 1)	$R_{\theta JA}$	57.7	
Junction−to−Ambient − Steady State (Note 2)	$R_{\theta JA}$	143.4	
Junction−to−Ambient − t = 10 sec	$R_{\theta JA}$	25	

1. Surface−mounted on FR4 board using 1 sq−in pad, 1 oz Cu.
2. Surface−mounted on FR4 board using the minimum recommended pad size.

ELECTRICAL CHARACTERISTICS (T_J = 25°C unless otherwise specified)

Parameter	Symbol	Test Condition		Min	Typ	Max	Unit
OFF CHARACTERISTICS							
Drain−to−Source Breakdown Voltage	$V_{(BR)DSS}$	V_{GS} = 0 V, I_D = 250 μA		30			V
Drain−to−Source Breakdown Voltage Temperature Coefficient	$V_{(BR)DSS}/T_J$				25		mV/°C
Zero Gate Voltage Drain Current	I_{DSS}	V_{GS} = 0 V, V_{DS} = 24 V	T_J = 25 °C			1	μA
			T_J = 125°C			10	
Gate−to−Source Leakage Current	I_{GSS}	V_{DS} = 0 V, V_{GS} = ±20 V				±100	nA
ON CHARACTERISTICS (Note 3)							
Gate Threshold Voltage	$V_{GS(TH)}$	V_{GS} = V_{DS}, I_D = 250 μA		1.5		2.5	V
Negative Threshold Temperature Coefficient	$V_{GS(TH)}/T_J$				5.6		mV/°C
Drain−to−Source On Resistance	$R_{DS(on)}$	V_{GS} = 10 V to 11.5 V	I_D = 30 A		4.7	7.0	mΩ
			I_D = 15 A		4.6		
		V_{GS} = 4.5 V	I_D = 30 A		9.2	11.4	
			I_D = 15 A		8.5		
Forward Transconductance	g_{FS}	V_{DS} = 15 V, I_D = 15 A			16		S
CHARGES AND CAPACITANCES							
Input Capacitance	C_{ISS}	V_{GS} = 0 V, f = 1 MHz, V_{DS} = 12 V			1436		pF
Output Capacitance	C_{OSS}				348		
Reverse Transfer Capacitance	C_{RSS}				177		
Total Gate Charge	$Q_{G(TOT)}$	V_{GS} = 4.5 V, V_{DS} = 15 V; I_D = 30 A			11.5	17	nC
Threshold Gate Charge	$Q_{G(TH)}$				2.0		
Gate−to−Source Charge	Q_{GS}				5.0		
Gate−to−Drain Charge	Q_{GD}				5.1		
Total Gate Charge	$Q_{G(TOT)}$	V_{GS} = 11.5 V, V_{DS} = 15 V, I_D = 30 A			25.4		nC
SWITCHING CHARACTERISTICS (Note 4)							
Turn−On Delay Time	$t_{d(ON)}$	V_{GS} = 4.5 V, V_{DS} = 15 V, I_D = 15 A, R_G = 3.0 Ω			13.5		ns
Rise Time	t_r				66.5		
Turn−Off Delay Time	$t_{d(OFF)}$				15.5		
Fall Time	t_f				7.5		

3. Pulse Test: pulse width ≤ 300 μs, duty cycle ≤ 2%.
4. Switching characteristics are independent of operating junction temperatures.

ELECTRICAL CHARACTERISTICS (T_J = 25°C unless otherwise specified)

Parameter	Symbol	Test Condition		Min	Typ	Max	Unit
SWITCHING CHARACTERISTICS (Note 4)							
Turn−On Delay Time	$t_{d(ON)}$	V_{GS} = 11.5 V, V_{DS} = 15 V, I_D = 15 A, R_G = 3.0 Ω			8.1		ns
Rise Time	t_r				24.2		
Turn−Off Delay Time	$t_{d(OFF)}$				22.8		
Fall Time	t_f				5.7		
DRAIN−SOURCE DIODE CHARACTERISTICS							
Forward Diode Voltage	V_{SD}	V_{GS} = 0 V, I_S = 30 A	T_J = 25°C		0.9	1.2	V
			T_J = 125°C		0.8		
Reverse Recovery Time	t_{RR}	V_{GS} = 0 V, dI_S/dt = 100 A/μs, I_S = 30 A			20.5		ns
Charge Time	t_a				11.6		
Discharge Time	t_b				8.9		
Reverse Recovery Charge	Q_{RR}				10.7		nC
PACKAGE PARASITIC VALUES							
Source Inductance	L_S	T_A = 25°C			0.93		nH
Drain Inductance	L_D				0.005		
Gate Inductance	L_G				1.84		
Gate Resistance	R_G				3.2		Ω

3. Pulse Test: pulse width ≤ 300 μs, duty cycle ≤ 2%.
4. Switching characteristics are independent of operating junction temperatures.

TYPICAL PERFORMANCE CURVES



Figure 1. On−Region Characteristics



Figure 2. Transfer Characteristics



Figure 3. On−Resistance vs. Gate−to−Source Voltage



Figure 4. On−Resistance vs. Drain Current and Gate Voltage



Figure 5. On−Resistance Variation with Temperature



Figure 6. Drain−to−Source Leakage Current vs. Voltage

TYPICAL PERFORMANCE CURVES



Figure 7. Capacitance Variation



Figure 8. Gate−To−Source and Drain−To−Source Voltage vs. Total Charge



Figure 9. Resistive Switching Time Variation vs. Gate Resistance



Figure 10. Diode Forward Voltage vs. Current



Figure 11. Maximum Rated Forward Biased Safe Operating Area



Figure 12. Maximum Avalanche Energy vs. Starting Junction Temperature

TYPICAL PERFORMANCE CURVES



Figure 13. EAS vs. Pulse Width



Figure 14. FET Thermal Response

PACKAGE DIMENSIONS

DFN5 5x6, 1.27P
(SO−8FL)
CASE 488AA
ISSUE G



NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETER.
3. DIMENSION D1 AND E1 DO NOT INCLUDE MOLD FLASH PROTRUSIONS OR GATE BURRS.

	MILLIMETERS		
DIM	MIN	NOM	MAX
A	0.90	1.00	1.10
A1	0.00	–––	0.05
b	0.33	0.41	0.51
c	0.23	0.28	0.33
D		5.15 BSC	
D1	4.50	4.90	5.10
D2	3.50	–––	4.22
E		6.15 BSC	
E1	5.50	5.80	6.10
E2	3.45	–––	4.30
e		1.27 BSC	
G	0.51	0.61	0.71
K	1.20	1.35	1.50
L	0.51	0.61	0.71
L1	0.05	0.17	0.20
M	3.00	3.40	3.80
θ	0 °	–––	12 °

STYLE 1:
PIN 1. SOURCE
2. SOURCE
3. SOURCE
4. GATE
5. DRAIN



SOLDERING FOOTPRINT*



*For additional information on our Pb−Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:
Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303−675−2175 or 800−344−3860 Toll Free USA/Canada
Fax: 303−675−2176 or 800−344−3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800−282−9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81−3−5817−1050

ON Semiconductor Website: **www.onsemi.com**

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative